REMOTE CONTROL PANEL FOR PM1127





The PM1122R is a remote control panel for the PM1122, APart's multifunctional preamplifier. Mounting screws are included.

The control panel offers music level control, line source selection and microphone mix level control.

The remote panels are connected to the PM1122 by a standard CAT-5 cable wired according to the T-568B protocol. The maximum wire length is up to 300m, according to circumstances. You can use one PM1122RL per zone.

TECHNICAL SPECIFICATIONS

Controls

Music and MicMix level control Music Selector control Power supply

General (PM1122R)

Dimensions H x W Shipping / Net weight Optional built-in and onwall boxes

<u>In wall back box - Ref. BBi1</u>

Dimensions :

On-wall back box - Ref. BB1 Dimensions:

0-10V operated DC operated

only via RJ-45 / CAT-5 to PM1122 main unit

 80×115 mm (40 mm depth behind panel) 220g/165g

compatible to Bticino 503 series

80 x 115 mm (40 mm depth behind panel)

80 x 114 x 48 mm



